

GAUGEMASTER®



MODEL 'WM2' DC ADAPTOR

FOR INDOORS USE ONLY

The power supply should be regularly examined for potential hazards such as damage to the casing, cable or plug etc. In the event of any damage to the casing of the unit it should be replaced. Repairs to damaged cable and connector should only be carried out by a qualified electrician. The unit should not be used until the damage has been repaired. The units are sealed and having no repairable components should not be opened.

Input: 220 – 240V AC at 50- 60Hz BS1363 flat pin moulded plug.
Output: Regulated 9V DC @ 1.6 Amps @ 25 deg C with overload protected


This unit is a smoothed and regulated SMPS and is ideal for use with electronic modules and components where the manufacturers specified a specific input range. DCC accessory units and Led drivers are some good examples.

This unit should not be used on items designed for unregulated power as this can result in poor operation or performance. A WM1 can be used on many unregulated devices and circuits.

Always check the manufacturer's specifications before connecting any power supply

CAUTION: It is very important that the outputs of two or more adaptors are not connected together in parallel. i.e. outputs linked. If done, there is a risk of electric shock from a plug not inserted into a socket.

In the event of an overload the unit will require time to cool before automatically restoring power. The output terminals provide the user with easy bare wire connection; please study the diagram below on terminals and connections.



GUARANTEE: The WM2 has a 12month guarantee and will be replaced free of charge any unit found defective by manufacture providing the item has not been tampered with. This guarantee covers only the supply of replacement, replacement parts, labour cost for fitting of same and the cost of returning the unit to the customer or retailer. This Guarantee does not affect your Statutory Rights. We reserve the right to vary design or specification without notice.

Gaugemaster Controls Ltd,
Gaugemaster House, Ford Road, Arundel, West Sussex BN18 0BN
Tel. No: 01903 884321 Fax. No: 01903 884377
Email: gaugemaster@gaugemaster.co.uk Web: www.gaugemaster.com
Registered in England. Reg. No: 2714470

